




JT – 200 Matching Transformer

Featuring:

- JT series Step up / Step down Transformers
- Offering low cost, flexible solutions to impedance matching
- 50 ohm to 200 ohm impedance transformation



The JT – 200 transformer works over a wide frequency band and allows you to increase the peak to peak voltage without having to increase the power of your RF amplifier. Due to the compact size, it can easily be placed in close proximity to the load and therefore minimize any losses due to the Q of your network.

Frequency Range

10 KHz – 5 MHz

Maximum Input Power

150 Watts

Input Impedance

50 ohms (nominal)

Output Impedance

200 ohms (nominal)

Input / Output Connectors

BNC

Temperature Range

0 – 40 C

120VAC required for cooling fan

Dimensions

150 x 80 x 60 mm



1387 Brighton Henrietta Townline Rd
Rochester, NY 14623
Tel: (585) 214 0598
Fax: (585) 214 0580
www.eandiltd.com